

### **AMENDMENTS TO THE CLAIMS**

The following listing of claims will replace all prior versions and listings of claims in the application.

1. **(Currently Amended)** A receiver in a fiber optic system configured to receive an optical signal of varying light intensity and to produce a data output signal proportional thereto, the receiver comprising:

an optical detector configured to receive the optical signal, the optical detector having a dynamic range of sensitivity between a high optical intensity value and a low optical intensity value, the optical detector further configured to convert the received optical signal into an analog electrical signal proportional to an optical intensity of the optical signal;

an electronic circuit coupled to the optical detector, the electronic circuit configured to receive the analog electrical signal from the optical detector and to produce digital data signals representative of the optical intensity of the optical signal such that the electronic circuit is configured to have an original maximum digital value proportional to the high optical intensity value and an original minimum digital value proportional to the low optical intensity value thereby defining an original receiver resolution between the original minimum and maximum digital values, and the electronic circuit further being configured such that a relative magnitude of the optical signal is represented at various points in time by a discrete number of digital values as an intelligent signal that comprises an output of the electronic circuit; and

an adjustment circuit coupled to the electronic circuit in parallel with the optical detector and configured to allow the original maximum digital value to be adjusted to an adjusted maximum digital value, the adjusted maximum digital value determined by a maximum value of the analog electrical signal and to allow the original minimum digital value to be adjusted to an adjusted minimum digital value, the adjusted minimum digital value determined by a minimum value of the analog electrical signal, thereby defining an adjusted receiver resolution between the adjusted minimum and maximum digital values.

2. **(Original)** The receiver of claim 1 wherein the adjusted maximum digital value is different than the original maximum digital value.

3. **(Original)** The receiver of claim 1 wherein the adjusted minimum digital value is different than the original minimum digital value.

4.       **(Original)**       The receiver of claim 1 wherein the adjusted maximum digital value is lower than the original maximum digital value and the adjusted minimum digital value is higher than the original minimum digital value such that the adjusted receiver resolution is finer than the original receiver resolution.

5.       **(Original)**       The receiver of claim 1 wherein the adjusted maximum digital value is proportional to a highest anticipated optical value for the optical signal received by the optical detector and wherein the adjusted minimum digital value is proportional to a lowest anticipated optical value of the optical signal received by the optical detector.

6.       **(Original)**       The receiver of claim 1 wherein the adjusted maximum digital value is less than the original maximum digital value and is proportional to a highest anticipated optical value for the optical signal received by the optical detector and wherein the adjusted minimum digital value is higher than the original minimum digital value is proportional to a lowest anticipated optical value of the optical signal received by the optical detector.

7.       **(Original)**       The receiver of claim 1 wherein the dynamic range of sensitivity is between a high optical intensity value of positive 7dBm and a low optical intensity value of negative 20dBm.

8.       **(Original)**       The receiver of claim 1 wherein the electronic circuit includes an analog-to-digital converter configured to receive the analog electrical signal and to convert the electrical signal into digital signals.

9.       **(Original)**       The receiver of claim 8 wherein the analog-to-digital converter converts the analog electrical signal into a series of 8-bit digital values.

10.      **(Original)**       The receiver of claim 9 wherein the lowest 8-bit digital value is originally the original minimum digital value and then adjusted to the adjusted minimum digital value, and wherein the highest 8-bit digital value is originally the original maximum digital value and then adjusted to the adjusted maximum digital value.

11. **(Original)** The receiver of claim 1 assembled into a intelligent small form factor pluggable module for use with a fiber optic system.

12. **(Currently amended)** A fiber optic communication system comprising:  
a signal transmitter that produces optical signals of varying light intensity;  
an optical fiber coupled to the signal transmitter that receives and transmits the optical signals;  
a receiver coupled to the optical fiber that receives the optical signals and produces a data signal proportional thereto, the receiver further comprising:

an optical detector configured to receive the optical signals, the optical detector having a dynamic range of sensitivity between a high optical value and a low optical value, the optical detector further configured to convert the received optical signals into electrical signals proportional to the optical intensity of the optical signals;

an electronic circuit coupled to the optical detector, the electronic circuit configured to receive the electrical signals from the optical detector and to have an initial digital range representative of the dynamic range, the initial digital range being defined between an initial maximum digital value and an initial minimum digital value, the initial maximum digital value being proportional to high optical value and the initial minimum digital value being proportional to low optical value; and

an adjustment circuit coupled to the electronic circuit configured to allow the initial maximum digital value to be adjusted to an adjusted maximum digital value and to allow the initial minimum digital value to be adjusted to an adjusted minimum digital value thereby defining an adjusted digital range, the adjusted maximum digital value being proportional to a highest anticipated optical value and the adjusted minimum digital value being proportional to a lowest anticipated optical value, wherein a number of steps of resolution between the adjusted minimum and maximum digital values is greater than a number of steps of resolution between the initial minimum and maximum digital values.

13. **(Original)** The fiber optic communication system of claim 12 wherein the adjusted maximum digital value is different than the initial maximum digital value.

14. **(Previously Presented)** The fiber optic communication system of claim 12 wherein the adjusted maximum digital value is lower than the initial maximum digital value and the adjusted minimum digital value is higher than the initial minimum digital value such that the adjusted digital range has more resolution than the initial digital range.

15. **(Original)** The fiber optic communication system of claim 12 wherein the electronic circuit includes an analog-to-digital converter configured to receive the analog electrical signal and to convert the electrical signal into a digital signal.

16. **(Original)** The fiber optic communication system of claim 12 wherein the receiver is assembled into an intelligent small form factor pluggable module for use in the fiber optic system.

17. **(Previously Presented)** A receiver in a fiber optic system, the receiver comprising:  
an optical detector configured to receive an optical signal of varying light intensity, the optical detector having a dynamic range of sensitivity between a high optical intensity value and a low optical intensity value, the optical detector further configured to convert the received optical signal into an analog electrical signal proportional to the optical intensity of the optical signal;

an electronic circuit coupled to the optical detector, the electronic circuit configured to receive the analog electrical signal from the optical detector and to produce digital signals representative of the optical intensity of the optical signal such that the electronic circuit is configured with an original maximum digital value proportional to the high optical intensity value and an original minimum digital value proportional to the low optical intensity value thereby defining an original receiver resolution between the original minimum and maximum digital values; and

adjustment means coupled to the electronic circuit for adjusting the original maximum digital value to an adjusted maximum digital value and for adjusting the original minimum digital value to an adjusted minimum digital value thereby defining an adjusted receiver resolution between the adjusted minimum and maximum digital values, wherein the adjusted maximum digital value and the adjusted minimum value are selected based on an anticipated minimum and maximum values of the analog electrical signal, and wherein the adjustment means is operable to adjust both a relative number of steps of resolution, as well as a relative width of steps of resolution.

Application No. 10/767,376  
Docket No. 16274.169  
Reply to Office Action mailed 1 April 2008

18. – 20. **(Canceled)**